

McAllan EG162



Premium 16-channel mixer with DSP effects and phantom power supply

Audio Inputs

	Qty	Type
Mic / Line mono	12	XLR - 1/4" jack
Mic / Line stereo	1	XLR - double 1/4" jack
Line stereo / MP3	1	Double 1/4" jack - SD card - USB
Line stereo	1	Double 1/4" jack
CD / Tape in	1	Double CINCH

Audio Outputs

Master	1	Double XLR
Booth	1	Double 1/4" jack
Tape	1	Double CINCH
Send	1	Double 1/4" jack
Phones Out	1	1/4" jack

Equalizer

Low	+/- 15dB @ 80 Hz
Mid	+/- 15dB @ 2,5 KHz
High	+/- 15dB @ 12 KHz

System specifications

Signal-to-noise ratio	> 95 dB
Crosstalk	> 70 dB
Distortion (THD)	< 0.03%
Frequency response	20 Hz - 30 kHz, +0/-1 dB

Power supply

Power consumption	32 W
Mains voltage	220-230 V(AC) - 50/60 Hz