

McAllan EG822



Premium 8-channel mixer with DSP effects and phantom power supply

Audio Inputs	Qty	Type
Mic / Line mono	4	XLR - 1/4" jack
Mic / Line stereo	1	XLR - double 1/4" jack
Line stereo / MP3	1	Double 1/4" jack - SD card - USB
Line stereo	1	Double 1/4" jack
CD / Tape in	1	Double CINCH
Audio Outputs		
Master	1	Double XLR
Booth	1	Double 1/4" jack
Tape	1	Double CINCH
Send	1	Double 1/4" jack
Phones Out	1	1/4" jack
Equalizer		
Low		+/- 15dB @ 80 Hz
Mid		+/- 15dB @ 2,5 KHz
High		+/- 15dB @ 12 KHz
System specifications		
Signal-to-noise ratio		> 95 dB
Crosstalk		> 70 dB
Distortion (THD)		< 0.03%
Frequency response		20 Hz - 30 kHz, +0/-1 dB
Power supply		
Power consumption		32 W
Mains voltage		220-230 V(AC) - 50/60 Hz